

The Fleet®

Unless otherwise noted, All voltage for all components of all systems 60Hz

Compressor Motor HP*	Phase	Voltage	Motor FLA	Recommended Fuses where field wired	Compressor mfg and model
30	3	208V***	40A***	AJT70	PDC4
30	3	230V***	40A***	AJT70	PDC4
30	3	460V	40A	AJT70	PDC4
30	3	575V	32A	AJT50	PDC4
30	3	380V (50hz)	51A	AJT90	PDC4

***150kVA Step-Up Transformer	Recommended Transformer Primary Fuses
***All 208/230VAC Systems will be manufactured as 480VAC and shipped with 150kVA step up transformer.	208V: AJT300
	230V: AJT250

*Motor overload will be set @Apeks to nameplate FLA. Recommended motor branch circuit fuse protection is 175% of NEC FLA from Table 430-250 per 430.52. Explanation here: http://www.cooperindustries.com/content/dam/public/bussmann/Electrical/Resources/solution-center/technical_library/BUS_Ele_Tech_Lib_Motor_Circuit_Notes.pdf

Control Panel	Goes with	Voltage	Phase	Main Fuse or breaker size	Recommended connection
	One per Force® 2 stage system	115VAC	1	10A	NEMA 5-15R wall receptacle with surge protector

Air Compressor	Goes with	Voltage	Phase	FLA	Recommended connection
5HP	Fleet® System	230VAC	1	22	30 amp Circuit with 6-30R receptacle

...continued on page 2

The Fleet®

...continued from page 1

Outdoor cooling unit	Goes with	Voltage	Phase	Full Load Amps from Advantage	Recommended connection
OACS30-Low Voltage	Up to three Force® 2 stage systems	208-230VAC	3	198	Field wired- 4/0 THHN (90c) to Fused disconnect @350A type J fuses
OACS 30- High voltage	Up to three Force® 2 stage systems	460VAC	3	93	Field wired- 2Ga THHN (90c) to Fused disconnect @150A type J fuses
OACS 30- Higher Voltage	Up to three Force® 2 stage systems	575VAC	3	73	Field Wired- 4Ga THHN (90C) to Fused disconnect @125A type J fuses
Indoor Temperature Control Units	Goes with	Voltage	Phase	Full Load Amps from Advantage	Recommended connection
Sentra SK-1035- Low voltage	Two per Force® 2 stage system	208-230VAC	3	28	Field wired- 10Ga THHN (90C) to Fused disconnect @40A Type J fuses
Sentra SK-1035- High voltage	Two per Force® 2 stage system	460VAC	3	14	Field wired- 14Ga THHN (90C) to Fused disconnect @20A type J fuses
Sentra SK-1035- Higher voltage	Two per Force® 2 stage system	575VAC	3	11.6	Field wired- 14Ga THHN (90C) to Fused disconnect @20A type J fuses



UL 508A Listed

U-54766